



BBC Microcomputer model B

1770 Disc Interface Upgrade Kit

Fitting Instructions

Within this publication the term 'BBC' is used as an abbreviation for 'British Broadcasting Corporation'.

©Copyright ACORN Computers Limited 1985

Neither the whole or any part of the information contained in, or the product described in, this manual may be adapted or reproduced in any material form except with the prior written approval of ACORN Computers Limited (ACORN Computers).

The product described in this manual and products for use with it, are subject to continuous development and improvement. All information of a technical nature and particulars of the product and its use (including the information and particulars in this manual) are given by ACORN Computers in good faith. However, it is acknowledged that there may be errors or omissions in this manual. A list of details of any amendments or revisions to this manual can be obtained upon request from ACORN Computers Technical Enquiries. ACORN Computers welcome comments and suggestions relating to the product and this manual.

All correspondence should be addressed to:-

Technical Enquiries
ACORN Computers Limited
Newmarket Road
Cambridge
CB5 8PD

All maintenance and service on the product must be carried out by ACORN Computers' authorised dealers. ACORN Computers can accept no liability whatsoever for any loss or damage caused by service or maintenance by unauthorised personnel. This manual is intended only to assist the reader in the use of this product, and therefore ACORN Computers shall not be liable for any loss or damage whatsoever arising from the use of any information or particulars in, or any error or omission in, this manual, or any incorrect use of the product.

ACORN is a trade mark of ACORN Computers Limited

First published 1985
Published by ACORN Computers

BBC MICROCOMPUTER MODEL B

1770 DISC INTERFACE

UPGRADE KIT

FITTING INSTRUCTIONS

Part No. 0433,050

Issue No.1

August 1985

CONTENTS

Section		Page
	FOREWORD	3
1	INTRODUCTION	4
1.1	General	4
1.2	Component Location	4
1.3	Integrated Circuit Pin Numbering	4
1.4	Removal of an Integrated Circuit	5
1.5	Insertion of an Integrated Circuit	5
2	DISMANTLING PROCEDURE	5
3	PRINTED CIRCUIT BOARD CONFIGURATIONS	6
4	FITTING THE 1770 DISC INTERFACE MODULE	6
5	FITTING THE 1770 DISC FILING SYSTEM ROM	7
6	REASSEMBLY PROCEDURE	9
7	TESTING THE COMPUTER	9
8	PRINTED CIRCUIT BOARD MODIFICATIONS	10

FOREWORD


These upgrade instructions are for the use of persons fitting the 1770 Disc Interface Module to any issue of the BBC microcomputer Model B. This 1770 disc upgrade is **NOT** suitable for the BBC microcomputer model B+. The upgrade kit should contain the following component parts:

1. These instructions.
2. 1770 Disc Interface Module.
3. 1770 Disc Filing System ROM.
4. 2 off 7438 Integrated Circuits.
5. 2 off Wire Links.
6. Acorn Disc Filing System User Guide and Addendum Sheet

Note: The wire links supplied with this kit are specifically designed to prevent damage to the IC sockets. Do not substitute any other components for these links.

These links may take one of a number of different designs as shown below. Please ensure that these items are identified and kept in a safe place until required.

Before attempting to carry out this upgrade it is important to first read the following instructions carefully.



1 INTRODUCTION

1.1 General

The BBC microcomputer model B main Printed Circuit Board currently stands at Issue 7. There should be no Issue 1 PCBs in the field, so these upgrade instructions will only cover upgrading Issues 2,3,4 and 7 (Issues 5 and 6 were never produced). There are no modifications required to the PCB for the Issue 4 and 7 boards, whereas Issues 2 and 3 may require modification. It is therefore important to identify the issue of the PCB before starting work. The issue number appears on the PCB in the silk screen legend just to the left of the board centre. If you look there you will see:

COPYRIGHT 1982 203,000 Issue X
A C O R N C O M P U T E R S Ltd

where X is the issue number.

1.2 Component location

It is necessary to understand the Acorn notation for locating a point on the PCB. This is done by considering the board as a compass. Position the PCB so that the components are facing upwards and the IDC headers (PLs 8,9,10,11 and 12) are closest to you. The edge furthest away from you (with the DIN sockets and modulator on it) is then NORTH, to your right is EAST, to your left is WEST and nearest is SOUTH.

1.3 Integrated circuit pin numbering

To install the 1770 module, an understanding of the pin numbering convention for integrated circuits is required.

With two exceptions, all ICs on the main PCB face NORTH, with pin one being located at the NORTH WEST corner of the chip. Pin one is indicated in one of two ways. Either a small dot or dimple is placed directly next to pin 1, or a half-moon shaped notch is cut into the pin 1 end of the IC, with pin 1 always being to the left of the notch when the notch is held uppermost. In some instances both of these indicators will be present.




Figure 1

The numbering sequence for a 14 pin device is shown in fig.1. As can be seen pin 1 is at the NORTH WEST corner, all the other pins are numbered consecutively in an anti-clockwise direction.

1.4 Removal of an integrated circuit

To avoid bending or breaking any pins, ICs must be removed very gently. Take a flat bladed screwdriver or similar tool and insert it between the body of the IC and the socket frame; gently prise up each end a bit at a time. Care must be taken to ensure that damage is not done to any PCB tracks that may be underneath the IC. Please note that frequent removal and insertion of an IC will inevitably lead to damage of both the IC and its socket.

1.5 Insertion of an integrated circuit

Before removing the IC from its protective packaging, identify pin 1 (see section 1.3).

Before inserting the IC into the socket first check to see if the legs of the IC are parallel with each other. If they appear crooked or splayed apart then they should be realigned. To do this hold the IC sideways on and press it gently against a firm flat surface, repeat for the other side of the IC.

Hold the ends of the IC between thumb and forefinger, and line up all the pins over the destination socket. Pin 1 should face to the NORTH (see section 1.2).

Apply firm pressure to the IC, but do not force it. When the chip is in place it may appear to be slightly raised. Check that all the pins have entered the socket and that none are bent either outwards or under the body of the IC.

2 DISMANTLING PROCEDURE

Before starting to dismantle the computer, first ensure that the unit is disconnected from the mains supply.

Locate and remove the four case fixing screws (sometimes labelled FIX); two are located at the rear and two underneath at the front.

Remove the upper half of the case.

Locate and remove the keyboard securing bolts; taking note of the assembly order of the nut and various washers. There will be either two or three of these bolts depending on the issue of the machine.

Unplug the 17 way keyboard ribbon cable from the main PCB at PL13. Care should be taken to ensure that the Molex strip at PL13 is not damaged.

Unplug the speaker lead from PL15.

If the Speech option is fitted to the machine, it will be necessary to unplug the 10 way ribbon cable from PL14.

The keyboard may now be removed from the machine.

3 PCB CONFIGURATIONS

Before commencing the upgrade it is necessary to check the following points. Check location IC 78 on the PCB for the presence of a 40 pin IC DIL socket. In the unlikely event that this socket is not present (either with or without the 8271 IC fitted), refer to section 8.

3.1 Check for the presence of a 14 pin IC DIL socket at location IC86. If a socket is not present, refer to section 8.

3.2 If the PCB is either an Issue 2 or an Issue 3, and a disc interface is not already installed, additional modifications are required, refer to section 8.

4 FITTING THE 1770 DISC INTERFACE MODULE

4.1 Locate link S9 which is located 1 inch to the WEST of pin 1 of IC78. If a wire link is fitted at this position, it must be cut using a small pair of wire cutters.

4.2 Locate ICs 79 and 80 which are situated directly to the SOUTH WEST of PL13 (the keyboard ribbon cable connector). If a disc interface was previously fitted to the machine, these two sockets will both contain ICs identified on top by the numbers 7438.

If a disc interface was not already fitted to the machine, these two ICs will be absent. In this instance insert the two 7438 ICs contained within the 1770 disc interface kit into these two sockets. Take care to follow the instructions on chip orientation and insertion contained within section 1.

4.3 Locate and remove the 8271 IC which is fitted at position IC78, the procedure for IC extraction is described in section 1.4.

4.4 If a socket is fitted at IC86, remove the 74LS393, taking care not to damage the socket or surrounding PCB.

Fit one of the wire links provided with the upgrade kit into socket IC86 connecting between pin 1 and pin 4 (see fig.2).

Locate position IC87. If this position is occupied by a 74LS123, the second link supplied with the upgrade should be disregarded. If the 74LS123 is not present the second link should be fitted between pins 9 and 12.




Figure 2

4.5 Having removed any anti-static foam or other padding, position the 1770 module such that the component side is faced downwards and position LK1 is at the bottom left.

Locate the two rows of pins on the underside of the 1770 module into the socket IC78. Ensure that the pins are all correctly lined up with the socket at IC78 before attempting to press the module into the socket.

When the module is correctly positioned it should obscure IC99 and RPl from view whilst leaving IC3 visible (see inside rear cover for component location diagram).

You may find it useful to use the foam pad, previously used to protect the pins on the 1770 module, to prevent injury to the hands when pressing down upon the module.

DO NOT USE EXCESSIVE FORCE WHEN PRESSING THE MODULE INTO PLACE. THIS COULD RESULT IN DAMAGE TO BOTH THE MODULE AND THE MAIN PCB.

5 FITTING THE 1770 DISC FILING SYSTEM ROM

The filing system ROMs are located at the SOUTH EAST corner of the main PCB as shown in fig.3.

It may be necessary to remove one of the existing filing system ROMs before fitting the 1770 DFS ROM. This depends on the filing system interface(s) already fitted, and the accompanying filing system ROM(s) fitted at that time.

Inserting ROMS – BBC Microcomputer Model B

This diagram shows a plan view of the BBC Microcomputer Model B. The top of the computer casing has been removed to reveal the four sideways ROM sockets. ROM software may be inserted in any of these sockets.




Figure 3

The options are:

ROM type	Filing system(s) already fitted	Action to be taken
0.90 DFS	DISC ONLY	Replace with 1770 DFS ROM.
0201,666-01 or 3.0 DNFS	DISC ONLY	Replace with 1770 DFS ROM.
As above	ECONET ONLY	ADD 1770 ROM to spare socket.
As above	DISC and ECONET	ADD 1770 ROM to spare socket.
2 ROMs : 0.90 DFS and 3.34 NFS	DISC and ECONET	Replace 0.90 DFS with 1770 ROM. Leave 3.34 NFS fitted.

For instruction on removal and insertion of ROMs or any other IC please refer to sections 1.4 and 1.5.

6 REASSEMBLY PROCEDURE

When the upgrade has been completed the unit should be reassembled as follows:

6.1 Ensure that no foreign objects are left inside the unit since they may cause shorting and damage to the unit after reassembly.

6.2 Reconnect the speaker lead to PL15

6.3 Reconnect the 17 way keyboard ribbon cable to PL13 taking care to ensure that the socket is correctly positioned (it is easy to offset the socket on the plug either one pin to the right or to the left).

6.4 If the Speech option is fitted, the 10 way ribbon cable must be connected to PL14. Care must again be taken to ensure that the socket is not offset on the plug.

6.5 Relocate the keyboard securing bolts and replace the washers and nuts in the correct order.

6.6 Replace the upper half of the case, relocate the four fixing screws and tighten them securely.

6.7 Check the working area to ensure that all components have been refitted to the unit and that nothing has been overlooked.

7 TESTING THE COMPUTER

When the upgrade has been completed and the unit has been reassembled connect the computer to a compatible disc drive in the manner described in the Acorn Disc Filing System User Guide.

Following the instructions contained within the Acorn Disc Filing System User Guide, prepare a disc for use and then attempt to load and save programs to and from the disc. If these operations can be carried out satisfactorily, it may be assumed that the upgrade was successful and that the disc interface is working correctly.

Any dealer performing this upgrade should test the completed unit using the Acorn PORT tester.

NOTE: Some pieces of commercial software may not function when used in conjunction with the 1770 disc interface. This is due to the nature of the protection employed by certain software houses. If this is the case then advice should be sought from the software supplier.

8 PRINTED CIRCUIT BOARD MODIFICATIONS

!WARNING PLEASE READ IN FULL!

THIS SECTION IS INTENDED FOR THE USE OF ACORN DEALER SERVICE PERSONNEL. MEMBERS OF THE PUBLIC SHOULD NOTE THAT ANY MODIFICATIONS CARRIED OUT TO THE PRINTED CIRCUIT BOARD OF ANY ACORN EQUIPMENT IS UNDERTAKEN AT THE SOLE RISK OF THE PERSON CARRYING OUT THE MODIFICATION. NO CLAIM FOR LOSS OR DAMAGE TO THE MICROCOMPUTER CAUSED THROUGH THE MODIFICATION OF THE PRINTED CIRCUIT BOARD BY UNQUALIFIED PERSONNEL SHALL BE ACCEPTED BY ACORN COMPUTERS LIMITED.

PLEASE READ ALL INSTRUCTIONS CAREFULLY. IF YOU ARE IN DOUBT ABOUT YOUR ABILITY TO CARRY OUT THE NECESSARY MODIFICATIONS, THE 1770 DISC UPGRADE MODULE, AND THE BBC MICROCOMPUTER SHOULD BE TAKEN TO YOUR NEAREST AUTHORISED ACORN DEALER.

A CHARGE MAY BE LEVIED BY THE DEALER FITTING THIS UPGRADE TO YOUR BBC MICROCOMPUTER; SUCH A CHARGE SHALL BE ENTIRELY AT THE DISCRETION OF THE DEALER CONCERNED.

8.1 Removing the main printed circuit board

Having removed both the upper half of the case and the keyboard assembly proceed as follows:

Disconnect the seven flying leads connecting the computers power supply to the main PCB, 3 red, 3 black and 1 purple.

Disconnect the two leads connecting the composite video socket (SK2) to the PCB.

Locate and remove the four (sometimes five or seven) PCB securing screws; two of which are situated on the SOUTH edge, one in the NORTH WEST corner and one in the NORTH EAST corner of the PCB.

The PCB may now be removed from the case by sliding it forwards and then lifting it from the rear.

Upon completion of all the necessary modifications, the PCB should be refitted by following the reverse of the above procedure. Having refitted the PCB the upgrade should be completed by following the procedure detailed in section 4.

8.2 Modification required when fitting a disc interface to an Issue 2 or 3 PCB

If the machine is fitted with an Issue 2 or 3 PCB then the following modification must be performed.

On the component side of the PCB, locate and cut the track connected to pin 9 of IC27. This cut should be made as close to IC27 as possible.

Locate and cut pin 9 of IC27. The cut should be made as close to the PCB as possible. If IC89 is fitted then its temporary removal will make this operation easier.

Bend pin 9 of IC27 into a horizontal position.

Solder a piece of insulated wire between pin 9 of IC27 and the EAST pad of link S9.

NOTE: Exercise extreme caution when making solder joints. Damage may easily be done to the IC when performing this operation.

8.3 Modification required where a socket is not fitted at position IC 86

There are three possible options:

1. Remove the PCB as detailed in section 8.1. Desolder and remove IC86 and fit a 14 pin DIL IC socket at position IC86. The upgrade may then be performed as described in section 4.

2. Remove the PCB as detailed in section 8.1. Locate and cut LK1 on the 1770 module. Using a piece of insulated wire, connect the pad of LK1 (indicated with an 'X' in fig.4), to the plate through hole directly to the NORTH of pin 1 of IC86 (see assembly diagram on inside back cover).

3. Locate and cut LK1 on the 1770 module. Using a piece of insulated wire, connect the pad of LK1 (as detailed in 2 above) to pin 1 of IC86.

If either option 2 or option 3 is used, the procedure detailed in section 4.1 is not required. If option 1 is used then section 4.1 still applies.

Option 3 is not recommended due to the likelihood of damage to the IC. Option 1 or 2 should be used in preference.

8.4 Modification required where a 40 pin DIL socket is not fitted at position IC78

Remove the PCB as detailed in section 8.1

Desolder and remove, where fitted, the 8271 disc controller IC.

Fit a 40 pin DIL IC socket at position IC78. Do NOT attempt to solder the 1770 disc interface module directly to the printed circuit board.

8.5 Upon completion of the appropriate modification(s), complete the installation of the upgrade as detailed in section 4.0.






Figure 4



MAIN PCB COMPONENT LAYOUT



Acorn Computers Limited, Fulbourn Road, Cherry Hinton, Cambridge CB1 4JN, England